

D48 / ID48 - Matrix Signal Processor Firmware Upgrade Guide



www.nstaudio.com

© NST Audio Ltd 2015

The latest firmware for the D48 / ID48 is included as part of the D-Net software that can be downloaded here:

http://www.nstaudio.com/software/dnet/D-Net\_Setup.exe

Ensure that you have the latest version of D-Net by going to the Help menu and click on "Check for Updates"

Go online to the D48 / ID48, open up the device control panel and click on the "System" page button. If a firmware upgrade is available, the "Upgrade Firmware" button will be visible, along with yellow text showing the new firmware version:

V C Unnamed Device		
	EQ Presets System View	Monitor
Information		
IP Address : 192.168.1.112 MAC Address : 252:194:61:10:246:197 Sample Rate : 96000 Firmware Version : 0.5.1.235		
Upgrade Firmware v0.5.1.236 ava	ailable	

Click on the "Upgrade Firmware" button, and the following dialog box will open:

	Upgrade Firmware	X
[		
	Load Firmware	_

Click on the "Load Firmware" button and then the "YES" button when the warning dialog appears:



After a short pause, while the firmware-upgrade process will start.

The progress bar will move as the new firmware is loaded:

Upgrade Firmware	
Load Firmware	

When the firmware loading is finished, another dialog box will appear:



At this point the unit will no longer pass audio or connect to the software!

Reboot the D48 / ID48 by power cycling the unit.



Go online to the unit and check that the firmware is now the latest version.

N.B. The "Upgrade Firmware" button should no longer appear.